

CSC 345 Lab – First Follow and First+ Sets

Overview

Calculate first, follow, and first+ sets.

Problem 1

Calculate Follow(E)

Start Symbol: E

$E \rightarrow i + i$

Problem 2

Calculate Follow(E), Follow(F)

Start Symbol: E

$E \rightarrow F + F$

$E \rightarrow F - F$

$F \rightarrow i$

Problem 3

Calculate First(E), First(S), First(T), First(V)

Start Symbol: E

$E \rightarrow S,$

$S \rightarrow T + S,$

$S \rightarrow T,$

$T \rightarrow V * T$

$T \rightarrow V$

$V \rightarrow 0,$

$V \rightarrow 1$

Problem 4

Calculate Follow(E), Follow(S), Follow(T), and Follow(V)
Start Symbol: E

$E \rightarrow S,$
 $S \rightarrow T + S$
 $S \rightarrow T$
 $T \rightarrow V * T$
 $T \rightarrow V$
 $V \rightarrow 0$
 $V \rightarrow 1$

Problem 5

Calculate First+ for each production
Start Symbol: S

$E \rightarrow S,$
 $S \rightarrow T + S,$
 $S \rightarrow T,$
 $T \rightarrow V * T$
 $T \rightarrow V$
 $V \rightarrow 0,$
 $V \rightarrow 1$

Problem 6

Calculate First+ for each production
Start Symbol: S

$E \rightarrow T Y$
 $Y \rightarrow + T Y$
 $Y \rightarrow \lambda$
 $T \rightarrow F Z$
 $Z \rightarrow * F Z$
 $Z \rightarrow \lambda$
 $F \rightarrow 0$
 $F \rightarrow 1$